



NOTES:

- A.** ALL CONDUIT BENDS ARE 36" RADIUS AND FULL 90° REQUIRING MINIMUM CONDUIT BURIAL DEPTH IN VICINITY OF SECTIONALIZER TO BE 47" BELOW FINAL GRADE.
- B.** CONDUIT INSTALLED FOR FUTURE CABLE RUNS SHALL EXTEND AT LEAST 24" BEYOND THE SECTIONALIZER AND BE CAPPED ON BOTH ENDS.
- C.** ALL CONDUITS AND GROUND ROD SHALL BE PLACED SUCH THAT THEY EMERGE IN FRONT HALF OF CABINET (LATCH SIDE OF DOOR).
- D.** KEEP ENCLOSURE TOP CLOSED AND LATCHED WHILE INSTALLING TO MAINTAIN ALIGNMENT UNTIL BACKFILLED.
- E.** ALL BACKFILL MATERIAL SHALL BE LUMP FREE AND COMPLETED BY HAND. ANY DAMAGE TO THE EQUIPMENT SHALL BE THE RESPONSIBILITY OF THE CUSTOMER/DEVELOPER.
- F.** CONSTRUCTION EQUIPMENT AND VEHICLES SHOULD BE KEPT MINIMUM OF 3 FEET AWAY FROM THE SECTIONALIZER TO PREVENT EXCESS PRESSURE ON THE BASE.

**3-PHASE 200A
SECTIONALIZER LOW-PROFILE**

DWG REV: 08/14/09 DWG: **760.1-3**